

10 POLI -poles-polig-600 min/-1 v 230/400 - Hz 50

| COD IMB3 - GRA | POTENZA NOMINA | VELOCITA' NOMI | INTENSITA' NOM | FATTORE DI POT | RENDIMENTOEFFE | CORRENTE D'AVV | COPPIA NOMINAL | COPPIA D'AVVIA | COPPIA MASSIMA | MOMENTO D'INER | PESOIMB3WEIGTI | |
|--------------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|----------------|--|
| R1003F1100 GR-132M | 1.5 | 540 | 4.5 Ĩ» | 0.81 | 82 | 6 | 26.7 | 1.2 | 3.5 | 0.07835 | 65 | |
| T1003F1100 GR-160M | 3 | 590 | 8 Ĩ» | 0.83 | 86 | 5 | 48.5 | 1.4 | 3.7 | 0.084321 | 80 | |
| T2003F1100 GR-160M | 4 | 580 | 12.5 Ĩ» | 0.82 | 84 | 5 | 65.3 | 1.1 | 3 | 0.12632 | 108 | |

