

12 POLI -poles-polig-500 min/-1 v 230/400 - Hz 50

COD IMB3 - GRA	POTENZA NOMINA	VELOCITA' NOMI	INTENSITA' NOM	FATTORE DI POT	RENDIMENTOEFFE	CORRENTE D'AVV	COPPIA NOMINAL	COPPIA D'AVVIA	COPPIA MASSIMA	MOMENTO D'INER	PESOIMB3WEIGTI		
C2003E1100 GR-71	0.02	420	0.5 Ĩ»	0.65	45.2	5	0.45	1.2	2.9	0.00131	7.5		
D5003E1100 GR-80	0.11	420	0.8 Ĩ»	0.62	44.5	5.2	2.54	1.4	3	0.00253	10.5		
D1003E1100 GR-80 **	0.15	430	1.2 Ĩ»	0.59	47.8	6	3.34	1.3	2.8	0.00291	12.8		
G4003E1100 GR-90S	0.24	430	1.3 Ĩ»	0.57	48.4	5.8	5.37	1.4	3.2	0.00486	26		
I4003E1100 GR-90L **	0.37	410	2.4 Ĩ»	0.50	48.8	5.7	8.43	1.1	2.9	0.00668	30		
M3003E1100 GR-100 **	0.55	440	2.6 Ĩ»	0.55	56.1	5.5	11.72	1	3	0.00786	36		
O1003E1100 GR-112	0.75	450	3.6 Ĩ»	0.51	64.2	5.4	15.51	1.1	3	0.00994	31		
R4003E1100 GR-132M	1.1	460	4.9 Ĩ»	0.48	69.9	6	22.6	1.1	2.9	0.0598	63.5		
R5003E1100 GR-132M **	1.5	460	5.5 Ĩ»	0.55	71.6	5.1	30.78	1.3	3.1	0.07835	67		
T1003E1100 GR-160M	1.84	470	6 Ĩ»	0.52	70.2	5.5	37.38	1.2	3.2	0.08432	80		
U1003E1100 GR-160L	2.2	460	7.5 Ĩ»	0.57	73.8	5.6	45.8	1.1	3	0.1263	108		